



Rev. D 15-Jan-14

DIMMER MAKE	DIMMER Series - Model	DIMMER TRIM REQUIREMENTS	TRANSFORMER MAKE Low Voltage Lamps	TRANSFORMER MODEL Low Voltage Lamps	LED LAMP OR LUMINAIRE Series - Model	MINIMUM LAMPS OR LUMINAIRES Per Circuit	MAXIMUM LAMPS OR LUMINAIRES Per Circuit	
Cooper	Rotary RI306P-VW-K2	N/A	N/A	N/A	PAR38 Series	1	7	
					PAR30 Series	1	7	
					PAR20 Series	1	5	
					MR16 GU10 Series	1	5	
Leviton	SureSlide 06633-761	N/A	N/A	N/A	PAR38 Series	1	7	
					PAR30 Series	1	7	
					PAR20 Series	1	5	
					MR16 GU10 Series	1	5	
	SureSlide 06674-722	N/A	N/A	N/A	N/A	PAR38 Series	1	3
						PAR30 Series	1	3
						PAR20 Series	1	2
						MR16 GU10 Series	1	2
	Rotary (1K3) RPI06-722	N/A	N/A	N/A	N/A	PAR38 Series	1	7
						PAR30 Series	1	7
						PAR20 Series	1	5
						MR16 GU10 Series	1	5
	Rotary (1C1) 06602-732	N/A	N/A	N/A	N/A	PAR38 Series	1	7
						PAR30 Series	1	7
						PAR20 Series	1	5
						MR16 GU10 Series	1	5
Likewise	52-8290-6	N/A	N/A	N/A	PAR38 Series	1	7	
					PAR30 Series	1	7	
					PAR20 Series	1	5	
					MR16 GU10 Series	1	5	
Lutron	Lumea LGCL-153PL	N/A	N/A	N/A	PAR38 Series	1	3	
					PAR30 Series	1	3	
					PAR20 Series	1	2	
					MR16 GU10 Series	1	2	
					PAR38 Series	1	7	
	Diva DV-603PG	N/A	N/A	N/A	N/A	PAR30 Series	1	7
						PAR20 Series	1	5
						MR16 GU10 Series	1	5
	Diva/Skylark/Skylark Contour/Ariadni/Toggler C-L wall-mount dimmers	N/A	N/A	N/A	N/A	PAR38 Series	1	8
						PAR30 Series	1	10
						PAR20 Series	1	16
						MR16 GU10 Series	1	26
	Maestro MACL-153M	N/A	N/A	N/A	N/A	PAR38 Series	1	8
						PAR30 Series	1	10
						PAR20 Series	1	16
						MR16 GU10 Series	1	26
	RadioRA 2 RRD-10ND	N/A	N/A	N/A	N/A	PAR38 Series	1	8
						PAR30 Series	1	10
						MR16 GU10 Series	1	26
	Maestro Wireless MRF2-6ND	N/A	N/A	N/A	N/A	PAR38 Series	1	8
						PAR30 Series	1	10
						PAR38 Series	1	8
	HomeWorks QS HQRD-6ND	N/A	N/A	N/A	N/A	PAR30 Series	1	10
						PAR38 Series	1	8
Home Works QS HQRD-10ND	N/A	N/A	N/A	N/A	PAR30 Series	1	10	
					MR16 GU10 Series	1	26	
					PAR30 Series	-	N/A	
Maestro Wireless MRF2-6ELV					PAR38 Series	1	9	
					PAR30 Series	1	10	
HomeWorks HxD-6ND	N/A	N/A	N/A	N/A	PAR20 Series	1	15	
					MR16 GU10 Series	1	24	



Rev. D 15-Jan-14

DIMMER MAKE	DIMMER Series - Model	DIMMER TRIM REQUIREMENTS	TRANSFORMER MAKE Low Voltage Lamps	TRANSFORMER MODEL Low Voltage Lamps	LED LAMP OR LUMINAIRE Series - Model	MINIMUM LAMPS OR LUMINAIRES Per Circuit	MAXIMUM LAMPS OR LUMINAIRES Per Circuit
	Stanza SZ-6ND	N/A	N/A	N/A	PAR38 Series	1	9
					PAR30 Series	1	10
					PAR20 Series	1	15
					MR16 GU10 Series	1	24
	PHPM-PA with Grafik Eye QS Main Unit	N/A	N/A	N/A	PAR38 Series	1	39
					PAR30 Series	1	39
					PAR20 Series	1	65
					MR16 GU10 Series	1	128
	PHPM-WBX with 3-wire fluorescent control	N/A	N/A	N/A	PAR38 Series	1	39
					PAR30 Series	1	39
					PAR20 Series	1	65
					MR16 GU10 Series	1	128
	Panel Module HW/LP-RPM-4A-120	N/A	N/A	N/A	PAR38 Series	1	24
					PAR30 Series	1	24
					PAR20 Series	1	41
					MR16 GU10 Series	1	80
	Panel Module HW/LP-RPM-4U-120	N/A	N/A	N/A	PAR38 Series	1	29
					PAR30 Series	1	35
					PAR20 Series	1	50
					MR16 GU10 Series	1	79
	Grafik QS Grafik Eye QS Main Unit Family	N/A	N/A	N/A	PAR38 Series	1	12
					PAR30 Series	1	14
					PAR20 Series	1	20
					MR16 GU10 Series	1	33
	Panel Module GP (Harrier) Card	N/A	N/A	N/A	PAR38 Series	1	29
					PAR30 Series	1	35
					PAR20 Series	1	50
					MR16 GU10 Series	1	79
	Maestro Sensor MSCL-OP153M(T2)*/MSCL-VP153M(T2)*	N/A	N/A	N/A	PAR38 Series	1	8
					PAR30 Series	1	10
					PAR20 Series	1	16
					MR16 GU10 Series	1	26
	Grafik Eye 3000 Grafik Eye 3000 Family	N/A	N/A	N/A	PAR38 Series	1	12
					PAR30 Series	1	14
					PAR20 Series	1	20
					MR16 GU10 Series	1	33
	Skylark S-603P	N/A	N/A	N/A	PAR38 Series	1	7
					PAR30 Series	1	7
					PAR20 Series	1	5



Rev. D 15-Jan-14

DIMMER MAKE	DIMMER Series - Model	DIMMER TRIM REQUIREMENTS	TRANSFORMER MAKE Low Voltage Lamps	TRANSFORMER MODEL Low Voltage Lamps	LED LAMP OR LUMINAIRE Series - Model	MINIMUM LAMPS OR LUMINAIRES Per Circuit	MAXIMUM LAMPS OR LUMINAIRES Per Circuit	
Pass & Seymour	Rotary 9673348S	N/A	N/A	N/A	MR16 GU10 Series	1	5	
					PAR38 Series	1	8	
					PAR30 Series	1	8	
					PAR20 Series	1	6	
					MR16 GU10 Series	1	6	
					PAR38 Series	1	8	
	Legrand Nickel 9673353S	N/A	N/A	N/A	N/A	PAR38 Series	1	8
						PAR30 Series	1	8
						PAR20 Series	1	6
						MR16 GU10 Series	1	6
						PAR38 Series	1	7
						PAR30 Series	1	7
Slide 9673340S	N/A	N/A	N/A	N/A	PAR20 Series	1	5	
					MR16 GU10 Series	1	5	
					MR16SO GX5.3	N/A	N/A	
					MR16SO GX5.3	N/A	N/A	
					MR16SO GX5.3	N/A	N/A	
					MR16SO GX5.3	N/A	N/A	
Leviton	Illumatech - IPE04-1LZ	N/A	Hatch LightTech LightTech	RS12-60M LET 60 LET 75	MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	
	VPE06-1LZ	N/A	Sea Gull Juno Con-Tech	96223S-15 TL601E-75 LA2075N	MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	
Lutron	Grafik Eye - GRX-3104-T w/ELVI-1000	High-end & Low-end	Hatch LightTech LightTech	RS12-60M LET 60 LET 75	MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	
	Grafik Eye - GRX-3104-T w/PHPM-PA-120	High-end & Low-end	Hatch LightTech LightTech	RS12-60M LET 60 LET 75	MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	
	Grafik Eye - GRX-3104-T w/PHPM-PA-120	High-end & Low-end	BEI	B0344F-4 REV.5	MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	
	Nova- NTELV-600	N/A	Hatch LightTech LightTech	RS12-60M LET 60 LET 75	MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	
	Radio-RRD-6NA	N/A	Sea Gull Juno Juno Fulham Lightech Con-Tech	96223S-15 TL602E-60 TL601E-75 PET-120-12-60 LET 60-LW LVT-300	MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	
					MR16SO GX5.3	N/A	N/A	
						N/A	N/A	
						N/A	N/A	



Rev. D 15-Jan-14

DIMMER MAKE	DIMMER Series - Model	DIMMER TRIM REQUIREMENTS	TRANSFORMER MAKE Low Voltage Lamps	TRANSFORMER MODEL Low Voltage Lamps	LED LAMP OR LUMINAIRE Series - Model	MINIMUM LAMPS OR LUMINAIRES Per Circuit	MAXIMUM LAMPS OR LUMINAIRES Per Circuit
Lutron	Nova - NLV-600	N/A	BEI	B0344F-4 REV.5	MR16SO GX5.3	N/A	N/A
Cooper	SI06P	N/A	Con-Tech	LVT-300		N/A	N/A
Leviton	Illumatech - IPE04-1LZ	N/A	Hatch	RS12-60M	MR16HO GX5.3	N/A	N/A
			LightTech	LET 60		N/A	N/A
			LightTech	LET 75		N/A	N/A
	VPE06-1LZ	N/A	Sea Gull	96223S-15	MR16HO GX5.3	N/A	N/A
			Juno	TL601E-75		N/A	N/A
			Con-Tech	LA2075N		N/A	N/A
Lutron	Grafik Eye - GRX-3104-T w/ELVI-1000	High-end & Low-end	Hatch	RS12-60M	MR16HO GX5.3	N/A	N/A
			LightTech	LET 60		N/A	N/A
			LightTech	LET 75		N/A	N/A
	Grafik Eye - GRX-3104-T w/PHPM-PA-120	High-end & Low-end	Hatch	RS12-60M	MR16HO GX5.3	N/A	N/A
			LightTech	LET 60		N/A	N/A
	Grafik Eye - GRX-3104-T w/PHPM-PA-120	High-end & Low-end	LightTech	LET 75	MR16HO GX5.3	N/A	N/A
			BEI	B0344F-4 REV.5		N/A	N/A
	Nova- NTELV-600	N/A	Hatch	RS12-60M	MR16HO GX5.3	N/A	N/A
			LightTech	LET 60		N/A	N/A
			LightTech	LET 75		N/A	N/A
	Radio-RRD-6NA	N/A	Sea Gull	96223S-15	MR16HO GX5.3	N/A	N/A
			Juno	TL602E-60		N/A	N/A
			Juno	TL601E-75		N/A	N/A
			Fulham	PET-120-12-60		N/A	N/A
			Lighttech	LET 60-LW		N/A	N/A
Con-Tech			LA2075N	N/A		N/A	
Nova - NLV-600	N/A	Con-Tech	LVT-300	MR16HO GX5.3	N/A	N/A	
		BEI	B0344F-4 REV.5		N/A	N/A	
		Con-Tech	LVT-300		N/A	N/A	
Cooper	SI06P	N/A	Con-Tech	LVT-300	MR16HO GX5.3	N/A	N/A
Cooper	DI06P	N/A	Con-Tech	LVT-300	MR16HO GX5.3	N/A	N/A